

ACT-500T UHF Bodypack Transmitter

Features

- Newly designed compact and lightweight housing for easy wearing.
- The panel integrates a backlit LCD and setup buttons for easy operation and view of all operating information.
- On top of the housing is equipped with an antenna, mute button and mini XLR connector. The Mini XLR audio input connector accepts either a screw-lock or a TA4F quick-lock plug. A remote-control mute jack is for easy activation of the mute function.
- The audio input can be switched to low impedance Mic-in “MT” or high impedance Line-in “GT” to match up the input impedance. The high dynamic range audio input prevents saturation distortion.
- The world’s first ACT™ function provides precise and rapid frequency sync to the receiver.
- The patented battery compartment can be inserted with two AA-type batteries or one rechargeable battery, charging via USB Type-C with the foolproof and safe charging circuit.
- A belt clip for easy wearing.



Specifications

Mic Capsule Modules	Paired with lavalier mic MU-55L or optional other MIPRO's lavalier and headworn mic capsule modules.
Max. Audio Input	0 dBV
Display	Green backlit LCD
Frequency Range	UHF 480 ~ 934 MHz (country dependent)
Bandwidth	24 MHz
Input Impedance Setting	Low impedance (Mic-in) and high impedance (Line-in) are switchable.
RF Power Output	10 mW / 50 mW switchable (country dependent)
Spurious Emission	< 4 nW
Battery	One 18500 lithium-ion battery or two AA alkaline
Charging Type	USB Type-C with the foolproof and safe charging circuit.
Dimensions	63 × 80 × 25 mm (W×H×D)
Weight	Approx. 96 g
Note	Refer to the actual product in the event of product discrepancy.



MIPRO Electronics Co., Ltd

Headquarters: 814 Beigang Road, Chiayi, 600079, Taiwan
Tel: +886.5.238.0809 | Fax: +886.5.238.0803
www.mipro.com.tw | mipro@mipro.com.tw

Specifications are subject to change without prior notice. MI022/01